BYOM Installation and Activation

Installation

Step 1. Update the firmware of your NovoConnect device (V4.5
or above)

• There are several ways to perform firmware update. Please refer to the corresponding document for details.

Step 2. Connect USB camera / microphone / soundbar to your Novo device



Step 3. Download and install the BYOM driver for your Windows and/or MacOS computers.

Please visit <u>www.launchnovo.com</u> for details.

Activation (First-Time Usage)

You will need to activate the BYOM feature on your Novo device for the very first-time usage. There are two ways to do so.

(1) Activation from your Novo device. Click on the main menu button and then **BYOM**. Follow the on-screen instructions to enter your **license key** or click **Free Trial** to gain access.

Novo Touch	★ New firmware is ready for upgrade	13:48
Contract of the second	Using Software Step 1 Connect to Meeting Room Wi-Fi NVC_E7D1D Step 2 Run "NoveConnect App" to start your presentation	Connection Method Scan QR Code Enter IP Address Novo-E7D1D ® 192.168.43.1 NVC_E7D1D BYOM Go to Menu -> BYOM to enable
		v4.5.1.1113 Corporate

(2) Activation via Remote Manager software.

Step1. Select the Novo device on the home screen and click on setting icon.

🔁 Remote Manage	r							- □ ×
C Device O Firmware Updat	te		Live	Hub 🛛 🕒 Announcen	nent 🔯 Preferences			V3.3.3.426
All Devices (1/15)	4	🗘 Refr	resh	Total: 15 () 😝 1 😝	0 😝 14)		Search	er 🗊 🖊
Unassigned Devices (0/5)				Room Name	IP Address	Group	Activity	Device Type
	1	Θ		Novo-32E6E	10.136.7.6	Group test	Idle	NovoDisplay DK XX1 Series
Group List: 🔻	2	θ	-	Novo-CED82	10.136.7.21		Offline	
	3							
	4							
	5							
	6							
	7							
	8							

Step 2. Click on "Activate" icon

Novo-2CEF32E6E (10.136.7.6)								
General Network Display	Audio Output	Home Screen	Security	Signage	Misc.			
Room Name	Novo-32E6E	<	Apply					
Model	ND-K2000							
Edition	Corporate							
App Version	v4.3.1.64 🕑 Online Update							
Build Version	ND-K2000-0064							
Software Edition	K2000-EU-CORP-ED	J						
Online Users	0	_						
BYOM	Not activated	6	• Activate					
O Refresh					Close			

Step 3. Enter your license key and then click on **"Apply"** icon to active your BYOM service.

Novo-2CEF32E6E (1	0.136.7.6)	
General Network	🏠 BYOM - Activate my license	X y Signage Misc.
Roon	Enter the license code to activate your software.	
	· · · · · ·	
Арр		Jpdate
Build	Apply Cancel	
Software	Edition K2000-EU-CORP-EDU	
Online	e Users 0	
	BYOM Not activated	Activate
O Refresh		Close

Step 4. Your BYOM service has been activated.

Novo-2CEF32E6E (10.136.7.6)								
General Network Display	Audio Output	Home Screen	Security	Signage	Misc.			
Room Name	Novo-32E6E		< Apply					
Model	ND-K2000							
Edition	Corporate							
App Version	v4.3.1.64	4	🗲 Online Upd	ate				
Build Version	ND-K2000-0064							
Software Edition	K2000-EU-CORP-EDU	J						
Online Users	0							
BYOM	Activated							
C Refresh					Close			
:=								

- <
- >