

NovoDS Synchronized Playback

Overview

Synchronized playback allows a group of NovoDS players the ability to display their content at the same timing. Typically, this is used in two application scenarios


- Multiple NovoDS players display the same content at the exact same timing. This is quite popular in exhibition halls, shopping malls, and museums, etc.
- Multiple NovoDS players are used to construct a video wall. In this case, each of NovoDS players plays its part of the video, and, with the exact same timing, their playback as a whole renders the full video flawlessly on the video wall.

The following video clip demonstrates the video playback synchronized by 2 NovoDS4k players.

Configuration

The basic concept of synchronized playback is to designate one player as the master unit and the rest synchronize their playback to this master unit. Time-sync signals are sent over the Ethernet to serve this purpose. (Note: WiFi is not

recommended due to its high rate of packet loss.)



The rest of this article describes how to configure this feature.

1. Identify the NovoDS players for the synchronized playback and connect them in the same Ethernet
2. Create a device group in NovoDS Studio.

Edit Group- [Video Wall]

Name: Enable Synchronized Playback

Description:

Devices:

<input checked="" type="checkbox"/>	Top-left	172.18.69.92	
<input checked="" type="checkbox"/>	Top-Right	172.18.69.98	
<input checked="" type="checkbox"/>	Bottom-Left	172.18.69.95	
<input checked="" type="checkbox"/>	Bottom-Right	172.18.69.99	
<input type="checkbox"/>	X700	172.18.69.73	Whaaat
<input type="checkbox"/>	NovoDisplay-EMEA	192.168.1.100	Whaaat
<input type="checkbox"/>	NRA Top	192.168.1.3	Test

























OK Cancel

3. Designate one of NovoDS players as the master unit and the rest automatically become follower units.

+ Group

Group List:

- Lobby
- Admin Building (1)
- School A
- School B (1)
- Test (3)
- Whaaat (2)
- Video Wall (4)**

Label	Name	IP Address	Playlist	Action
● Top-Right		172.18.69.98		     
● Top-left		172.18.69.92		     
● Bottom-Right		172.18.69.99		     
● Bottom-Left		172.18.69.95		     

After connecting the device, click this button to "set as master unit"

4. Upload content (playlists) to all NovoDS players. For video wall applications, it is likely that each player has its unique playlist as each player only plays a part of the video

and as a whole, their synchronized playback becomes a full video.

5. Start the playback of the master unit, and the follower units will start their playback automatically.