2.7 Use Remote Manager for installation

Launch **Remote Manager** software under the same local network with Novo device.

Go the the left topper corner, click **+Deivce** > Input the Novo device's IP address to add the device into Remote Manager table.



One the device list, click the device you want to configure, then click to go to setup.

0	Refr	resh 🛛 Total: 71 (🛛 😜 🗆	(🤤 7 😝 0 😝 64) Search						
	•	Device Name	IP Address	rou	Activity	Device Type	Firmware Version	WI-FI M	ac Address 📤
1	\bigcirc	Novo-DE271	10.136.5.20		Idle	NovoTouch EK-II Ser	v4.1.0.1024	50:2B:73:	DD:13:0A
2	\bigcirc	Novo-D831G	10.136.5.126		Idle	NovoPro	v2.7.4.422	04:E6:76:	C3:33:78
3		Novo-16016	10.136.5.17		Idle	NovoTouch LK Series	v3.1.1.284	10:D0:7A	:71:BB:47

IT can control the devices remotely, such as setup device name, remote upgrade, change system language and time zone, download log file remote for troubleshooting and so on for individual Novo device.

Novo-B5CADE271 (10.136.5.20)					
General Network Securit	y Misc.				
Device Name	Novo-DE271	≺ Apply			
Model	NT-C2100-WFS0860				
Edition	Corporate				
App Version	v4.1.0.1024	🕑 Online Update			
Build Version	NovoTouch-C2100-0049				
Software Edition	C2100-WW-CORP-EDU				
Online Users	0				
O Refresh			Close		

General settings

Novo-B5CADE271 (10.136.5.20)			
General Network Security Misc.			
Wi-Fi Mode HotSpot	🔗 Configure Wi-Fi		
SSID NVC_DE271			
Wi-Fi IP 192.168.43.1	罕 Network Routing		
LAN IP 10.136.5.20			
WI-FI Mac Address 50:2B:73:DD:13:0A			
LAN Mac Address C0:8A:CD:DE:E5:30			
O Refresh	Close		

Network settings



Security settings

General Network Securit	ty Misc.	
Display		
Language	English	
Time Zone	Pacific Time (GMT-7:00)	≺ Apply
NTP Settings		
System Time	2020/06/30 02:02:56 PDT	
NTP Server	2.android.pool.ntp.org	≺ Apply 3 Reset
Log Download		
	Enable Log Download	< Apply
Restart Device		
	3 Reboot Now	
Configure Device		
	• Upload Configuration File	

Settings for System Language, Time Zone, NTP Server, Log File Download, Remote Reboot, Upload Config File.